

EKM METERING

6 Digit LCD Pulse Counter

Function: Simple Pulse Counter

Pulse Ratio: 1:1

Battery: 1.5V Watch Battery Included

Battery Life: 6 Years

Our battery powered pulse counter keeps track of one of our pulse output devices. With this device installed, you will know how much water, gas, or electricity you are using from up to 200 feet away from your pulse output meter. If you disconnect the battery the counter will reset to zero.

Battery Replacement Instructions:

The batteries previously installed in these pulse counters do not have a charge. A replacement battery is included for your convenience.

To replace the battery see the pictures for a reference and follow these instructions.

1. Turn Pulse Counter over to reveal battery and circuit board on back.
2. Separate the two halves of the plastic housing at the seam. The housing will slip off of the counter allowing you to install the battery.
3. Using a screwdriver or similar object, gently push battery out of metal battery retainer on Pulse Counter.
4. Locate replacement battery and install with flat side (+) facing up (away from the front LCD screen).
5. Turn Pulse Counter back over and it is ready for use. Every time the contacts (wires) connect, or the Meter they are connected to connects their circuit, the Pulse Counter will increment forward. You can test this by touching the wires together – the LCD should increment forward every time they touch.

More info available at:

documents.ekmmetering.com/LCD-Pulse-Counter.pdf

www.ekmmetering.com 831.425.7371 Santa Cruz, California info@ekmmetering.com

