

Send
2F 3F 30 30 30 30 30 30 30 30 30 30 32 32 32 30 30
21 0D 0A

Receive
02 10 24 15 30 30 30 30 30 30 30 30 30 32 32 32
30 30 33 32 38 35 35 32 30 30 30 33 33 32 33 32
30 30 30 30 30 30 33 34 30 30 31 31 37 39 34 30
30 30 31 30 35 32 34 35 30 30 31 30 35 33 32 31
30 30 30 30 30 30 31 36 30 30 30 30 30 30 30 39
30 30 30 30 30 30 39 30 30 33 32 38 35 35 32
30 30 30 30 30 30 33 34 31 32 30 37 31 32 31 31
31 32 31 30 30 30 37 34 30 30 30 34 30 30 30
30 34 30 30 30 30 38 32 36 30 30 30 30 34 38
32 30 30 30 30 34 38 32 30 30 30 31 37 39 32 30
31 30 30 30 31 30 30 30 31 30 30 30 30 30 30
34 34 30 30 30 30 30 32 34 30 30 30 30 30 32 36
30 30 30 30 30 39 36 36 30 30 33 30 30 30 30
30 31 36 30 30 30 30 30 30 30 30 30 30 30 30
30 31 39 30 38 31 32 30 30 31 33 30 36 31 36 30
31 31 32 33 30 34 34 30 30 21 0D 0A 03 10 21

Send
2F 3F 30 30 30 30 30 30 30 30 30 30 32 32 32 30 31
21 0D 0A

Receive
02 10 24 15 30 30 30 30 30 30 30 30 30 32 32 32
30 30 31 39 34 34 37 31 30 30 30 36 39 30 39 30
30 30 30 36 34 31 39 31 30 30 30 30 30 30 30
30 30 30 30 30 30 33 34 30 30 30 30 30 30 30
30 30 30 30 30 30 30 30 30 30 30 30 30 30 30
31 32 30 37 31 32 31 31 31 32 31 30 30 30 30 37
34 30 30 34 30 30 30 30 34 30 30 30 30 30 38
32 36 30 30 30 30 34 38 32 30 30 30 30 34 38 32
30 30 30 31 37 39 32 20 31 30 30 20 31 30 30 20
31 30 30 30 30 30 32 34 37 30 30 31 30 30 30 31
30 30 30 33 30 30 30 35 30 32 30 30 30 30 38 30
30 30 30 30 30 30 30 30 30 30 30 30 30 30 30
30 30 30 30 30 30 30 30 30 30 30 30 30 30 30
30 30 30 30 30 30 30 30 31 33 30 36 31 36 30
31 31 32 33 30 34 34 30 31 21 0D 0A 03 50 2B

Send
01 42 30 03 75

Data	Value
Model	EKM-Omnimeter Pulse v.4
Firmware	15
Address	222
Total Kilowatt Hour	3285.52
Forward Kilowatt Hour	3285.18
Reverse Kilowatt Hour	0.34
Net Kilowatt Hour	3284.84
Total Kilowatt Hour T1 (TOU1)	1944.71
Total Kilowatt Hour T2 (TOU2)	698.90
Total Kilowatt Hour T3 (TOU3)	641.91
Total Kilowatt Hour T4 (TOU4)	0.00
Reverse Kilowatt Hour T1	0.34
Reverse Kilowatt Hour T2	0.00
Reverse Kilowatt Hour T3	0.00
Reverse Kilowatt Hour T4	0.00
Voltage1	120.7
Voltage2	121.1
Voltage3	121.0
Current1 (Amps1)	7.4
Current2 (Amps2)	4.0
Current3 (Amps3)	4.0
Power1 (Watts1)	826
Power2 (Watts2)	482
Power3 (Watts3)	482
Total Power (Watts)	1792
Cosθ 1 (Power Factor1)	1.00
Cosθ 2 (Power Factor2)	1.00
Cosθ 3 (Power Factor3)	1.00
Max Demand	2470
Max Demand Period	15 Minutes
CT Ratio	200
Pulse 1 Count	16
Pulse 1 Ratio	1
Pulse 2 Count	9
Pulse 2 Ratio	3
Pulse 3 Count	19
Pulse 3 Ratio	5
Reactive Kilowatt Hour (kVARh)	332.32
Total Kilowatt Hour L1	1179.40
Total Kilowatt Hour L2	1052.45
Total Kilowatt Hour L3	1053.21
Reverse Kilowatt Hour L1	0.16
Reverse Kilowatt Hour L2	0.09
Reverse Kilowatt Hour L3	0.09
Resettable Total Kilowatt Hour	3285.52
Resettable Reverse Kilowatt Hour	0.34
Reactive Power L1 (VARs)	44
Reactive Power L2	24
Reactive Power L3	26
Total Reactive Power	96
Frequency (Hz)	60.03
Pulse Input State 1	Open
Pulse Input 2	Open
Pulse Input 3	Open
Current Direction L1	Reverse
Current Direction L2	Reverse
Current Direction L3	Reverse
Output 1	Off
Output 2	Off
Decimal Places	2
Auto Reset Max Demand	Off
Settable Pulse Output Ratio (Pulses Per kWh)	800
Checksum	502B